

**AVIPC351J 5 IR IP Camera (Normal LED)**

	<p><b>Feature</b></p> <ul style="list-style-type: none"> <li>◆ Sensor Resolution: 420TVL</li> <li>◆ Lens Type(Optical zoom Capability): 6.0mm fixed lens</li> <li>◆ IR LED: 8 § IR LED x 14pcs</li> <li>◆ Video Compression: 4 video profiles simultaneously             <ol style="list-style-type: none"> <li>1) MPEG4 VGA</li> <li>2) MPEG4 QVGA</li> <li>3) MPEG4 QQVGA</li> <li>4) MJPEG VGA/ QVGA/ QQVGA (selectable)</li> </ol> </li> <li>◆ IR Distance: 20-25 meter</li> <li>◆ Resolution: 640*480/ 320*240/ 160*120</li> <li>◆ UPnP Level: UPnP Discover &amp; Auto port forwarding</li> </ul>
--	---

**Specifications**

Model No.	AVIPC351J
<b>LAN</b>	10/100MB
<b>Video/ Audio</b>	
Image Sensor	1/3" Sony CCD
Sensor Resolution	420TVL
Lens Type(Optical zoom Capability)	6.0mm fixed lens
<b>IR LED</b>	<b>8 § IR LED x 14pcs</b>
IR Distance	20-25 meter
Video Compression	4 video profiles simultaneously 1) MPEG4 VGA 2) MPEG4 QVGA 3) MPEG4 QQVGA 4) MJPEG VGA/ QVGA/ QQVGA (selectable)
Resolution	640*480/ 320*240/ 160*120
Image Frame Rate	Max. 30 fps(N), 25fps (P) for all resolutions
2-way Audio	Simplex / Duplex 2-way audio
3GPP Cell Phone	3GPP mobile surveillance. Audio+video
<b>System</b>	
OS	WindowsR 2000, XP, Vista

Browser	IE 6.0 or latter
Easy DDNS Service	DIPS®
UPnP Level	UPnP Discover & Auto port forwarding
I/O port	
DI/ DO Ports	DI:1/DO:1
RS-485	RS485 for PT scanner
Video Output	BNC video output
Audio Input/Output	Line in/Line Out
Motion Detection	4 zones
Pre-recording	v
Send E-Mail/ FTP	v
Voice Alert	v
Construction	IP66 weather proof
NVR Software	
Bundle	16ch. "SecuGuard Basic"
Professional	16ch. SecuGuard Lite, and 64ch. SecuGuard Pro.